

20Watt Power Amplifier **MAP202** (EMS 시험용)



Frequency range	80 to 1000MHz
Gain	46dB typ @ 80 to 600MHz 44.5dB typ @ 600 to 1000MHz
1dB compression level	42.5dBm typ @ 80 to 600MHz 41dBm typ @ 600 to 1000MHz
Input VSWR	less than 2.0
Output VSWR	less than 5.5
Maximum input level	+20dBm
Modulation output	50Ω
Input/Output connectors	N (J) @ INPUT, OUTPUT
Power supply voltage	100 to 240VAC, 50 to 60Hz
Power consumption	approx. 80VA @ maximum output
Dimensions	430(W)×150(H)×440(D)mm (excluding projections)
Weight	approx. 10kg